

Computer Science & Information Technology

Discrete and Engineering Mathematics

Comprehensive Theory

with Solved Examples and Practice Questions



MADE EASY
Publications



MADE EASY Publications Pvt. Ltd.

Corporate Office: 44-A/4, Kalu Sarai (Near Hauz Khas Metro Station), New Delhi-110016

E-mail: infomep@madeeasy.in

Contact: 011-45124660, 8860378007

Visit us at: www.madeeasypublications.org

Discrete and Engineering Mathematics

© Copyright by MADE EASY Publications Pvt. Ltd.

All rights are reserved. No part of this publication may be reproduced, stored in or introduced into a retrieval system, or transmitted in any form or by any means (electronic, mechanical, photo-copying, recording or otherwise), without the prior written permission of the above mentioned publisher of this book.

First Edition: 2015

Second Edition : 2016

Third Edition : 2017

Fourth Edition : 2018

Fifth Edition : 2019

Sixth Edition : 2020

Seventh Edition : 2021

Eighth Edition : 2022

Contents •

Discrete and Engineering Mathematics

Chapter 1

Propositional Logic 3

- 1.1 Propositional Logic; First Order Logic..... 3
- 1.2 Logical Connectives or Operators..... 3
- 1.3 Well-Formed Formulas (WFFs) 8
- 1.4 Normal forms of Well-Formed Formulas 10
- 1.5 Rules of Inferences for Propositional Calculus ... 12
- 1.6 Predicate Calculus 13
- 1.7 Universal and Existential Quantifiers 14
- Student Assignments* 17

Chapter 2

Combinatorics 21

- 2.1 Introduction..... 21
- 2.2 Permutations 22
- 2.3 Combinations..... 25
- 2.4 Binomial Identities..... 27
- 2.5 Generating Functions..... 29
- 2.6 Summation..... 30
- 2.7 Recurrence Relations..... 33
- 2.8 Solving Recurrence Relations..... 34
- Student Assignments* 39

Chapter 3

Set Theory and Algebra 44

- 3.1 Introduction..... 44
- 3.2 Sets..... 44
- 3.3 Relations..... 49
- 3.4 Functions 59
- 3.5 Equal Functions 65
- 3.6 Groups 65
- 3.7 Lattice..... 73

- 3.8 Types of Lattices..... 78

- 3.9 Boolean Algebra..... 80

Student Assignments 82

Chapter 4

Graph Theory 93

- 4.1 Fundamental Concepts 93
- 4.2 Special Graphs 97
- 4.3 Graph Representations 99
- 4.4 Isomorphism..... 100
- 4.5 Invariants of Isomorphic Graphs 101
- 4.6 Operations on Graphs 102
- 4.7 Walks, Paths and Cycles 103
- 4.8 Connected Graphs, Disconnected Graphs
and Components 104
- 4.9 Euler Graphs 108
- 4.10 Hamiltonian Graphs..... 108
- 4.11 Planar Graphs 109
- 4.12 Trees..... 110
- 4.13 Enumeration of Graphs 115
- Student Assignments* 122

Chapter 5

Probability..... 126

- 5.1 Some Fundamental Concepts..... 126
- 5.2 Mean..... 130
- 5.3 Median..... 131
- 5.4 Mode and Standard Deviation..... 133
- 5.5 Standard Deviation 133
- 5.6 Random Variables..... 135
- 5.7 Distributions..... 135
- Student Assignments* 141

Chapter 6

Linear Algebra 148

6.1	Introduction.....	148
6.2	Special Types of Matrices	148
6.3	Algebra of Matrices	149
6.4	Properties of Matrices	151
6.5	Determinants	153
6.6	Inverse of Matrix.....	156
6.7	System of Linear Equations.....	157
6.8	Solution of System of Linear Equation by LU Decomposition Method (Factorisation or Triangularisation Method).....	159
6.9	Eigenvalues and Eigenvectors	162
	<i>Student Assignments</i>	168

Chapter 7

Calculus..... 175

7.1	Limit.....	175
7.2	Continuity.....	179
7.3	Differentiability.....	180
7.4	Mean Value Theorems.....	181
7.5	Theorems of Integral Calculus.....	184
7.6	Methods of Integration.....	184
7.7	Definite Integrals.....	187
7.8	Partial Derivatives.....	191
7.9	Total Derivatives.....	193
7.10	Maxima and Minima (of function of a single independent variable)	194
	<i>Student Assignments</i>	201



Discrete & Engineering Mathematics

Goal of the Subject

The mathematics of modern computer science is built almost entirely on discrete math, in particular Combinatorics and graph theory. Discrete math will help you with the “Algorithms, Complexity and Computability Theory” part of the focus more than programming language. The understanding of set theory, probability, matrices and combinations will allow us to analyze algorithms. We will be able to successfully identify parameters and limitations of your algorithms and have the ability to realize how complex a problem/solution is.

Discrete & Engineering Mathematics

INTRODUCTION

In this book we tried to keep the syllabus of Discrete & Engineering Mathematics around the GATE syllabus. Each topic required for GATE is crisply covered with illustrative examples and each chapter is provided with Student Assignment at the end of each chapter so that the students get a thorough revision of the topics that he/she had studied. This subject is carefully divided into eight chapters as described below.

Discrete Mathematics:

1. **Propositional Logic:** In this chapter we study logical connectives, well-Formed formulas, rules for inference, predicate calculus with Universal and Existential quantifiers.
2. **Combinatorics:** In this chapter we discuss the basic principles of counting, permutations, combinations, generating functions, binomial coefficients, summations and finally we discuss the recurrence relations.
3. **Set Theory and Algebra:** In this chapter we discuss the basic terms and definitions of set theory, Operations on sets, relations and types of relations, functions and their types and finally group theory, posets, lattices and boolean algebra.
4. **Graph Theory:** In this chapter we discuss the Special Graphs, isomorphism, vertex and edge connectivity, Euler graphs, Hamiltonian and planar graph, trees and enumeration of graphs.

Engineering Mathematics:

5. **Probability:** In this chapter we discuss the basic probability and axioms of probability, Basic concepts of statistics (mean, mode, variance and standard deviation), Discrete and continuous random variables and their distributions.
6. **Linear Algebra:** In this chapter we discuss the Special matrices, Algebra of matrices and their properties, inverse of a matrix, determinant of a matrix, solution of system of linear equations, LU decomposition method, Eigen values and Eigen vectors and finally we discuss the Cayley Hamilton theorem.
7. **Calculus:** In this chapter we discuss about Limits, continuity and differentiability, differentiation, partial derivatives, applications of differentiation (Mean value theorems, increasing and decreasing functions and maxima and minima of functions), methods of integration, and finally definite and indefinite integrals and their properties.




Propositional Logic

1.1 Propositional Logic; First Order Logic

Logic: In general logic is about reasoning. It is about the validity of arguments. Consistency among statements and matters of truth and falsehood. In a formal sense logic is concerned only with the form of arguments and the principle of valid inferencing. It deals with the notion of truth in an abstract sense.

Truth Tables: Logic is mainly concerned with valid deductions. The basic ingredients of logic are logical connectives, and, or, not, if.... then, if and only if etc. We are concerned with expressions involving these connectives. We want to know how the truth of a compound sentence like, " $x = 1$ and $y = 2$ " is affected by, or determined by, the truth of the separate simple sentences " $x = 1$ ", " $y = 2$ ".

Truth tables present an exhaustive enumeration of the truth values of the component propositions of a logical expression, as a function of the truth values of the simple propositions contained in them. An example of a truth table is shown in table 1 below. The information embodied in them can also be usefully presented in tree form.



The branches descending from the node A are labelled with the two possible truth values for A. The branches emerging from the nodes marked B give the two possible values for B for each value of A. The leaf nodes at the bottom of the tree are marked with the values of $A \wedge B$ for each truth combination of A and B.

1.2 Logical Connectives or Operators

The following symbols are used to represent the logical connectives or operators.

And	\wedge (Conjunction)
or	\vee (Disjunction)
not	\neg (Not)
Ex - or	\oplus
Nand	\uparrow
Nor	\downarrow
if....then	\rightarrow (Implication)
ifandonlyif	\leftrightarrow (Biconditional)

1. **\wedge (And / Conjunction):** We use the letters F and T to stand for false and true respectively.

Table-1

A	B	$A \wedge B$
F	F	F
F	T	F
T	F	F
T	T	T

It tells us that the conjunctive operation \wedge is being treated as a **binary** logical connective—it operates on two logical statements. The letters A and B are “**Propositional Variables**”.

The table tells us that the compound proposition $A \wedge B$ is true only when both A and B are true separately. The truth table tells us how to do this for the operator. $A \wedge B$ is called a truth function of A and B as its value is dependent on and determined by the truth values of A and B.

A and B can be made to stand for the truth values of propositions as follows:

A : The cat sat on the mat

B : The dog barked

Each of which may be true or false. Then $A \wedge B$ would represent the compound proposition “The cat sat on the mat and the dog barked”

$A \wedge B$ is written as A.B in Boolean Algebra.

2. **\vee (Disjunction):** The truth table for the disjunctive binary operation \vee tells us that the compound proposition $A \vee B$ is false only if A and B are both false, otherwise it is true.

A	B	$A \vee B$
F	F	F
F	T	T
T	F	T
T	T	T

This is inclusive use of the operator ‘or’.

In Boolean Algebra $A \vee B$ is written as $A + B$.

3. **\neg (Not):**

The negation operator is a “**unary operator**” rather than a binary operator like \wedge and its truth table is

A	$\neg A$
F	T
T	F

The table presents \neg in its role i.e., the negation of true is false, and the negation of false is true. Notice that $\neg A$ is sometimes written as $\sim A$ or A' .

4. \oplus (Exclusive OR or Ex - OR):

$A \oplus B$ is true only when either A or B is true but not when both are true or when both are false.

$A \oplus B$ is also denoted by $A \vee - B$.

A	B	$A \oplus B$
F	F	F
F	T	T
T	F	T
T	T	F

5. \uparrow (NAND):

$$P \uparrow Q \equiv \neg (P \wedge Q)$$

6. \downarrow (NOR):

$$P \downarrow Q \equiv \neg (P \vee Q)$$

Note:

$$P \uparrow P \equiv \neg P$$

$$P \downarrow P \equiv \neg P$$

$$(P \downarrow Q) \downarrow (P \downarrow Q) \equiv P \vee Q$$

$$(P \uparrow Q) \uparrow (P \uparrow Q) \equiv P \wedge Q$$

$$(P \uparrow P) \uparrow (Q \uparrow Q) \equiv P \vee Q$$

7. \rightarrow (Implication):

A	B	$A \rightarrow B$
F	F	T
F	T	T
T	F	F
T	T	T

Note that $A \rightarrow B$ is false only when A is true and B is false. Also, note that $A \rightarrow B$ is true, whenever A is false, irrespective of the truth value of B.

8. \leftrightarrow (if and only if): The truth table is

A	B	$A \leftrightarrow B$
F	F	T
F	T	F
T	F	F
T	T	T

Note that Bi-conditional (if and only if) is true only when both A & B have the same truth values.

($A \leftrightarrow B$ may be written as $A \rightleftharpoons B$)

Equivalences: $B \wedge A$ always takes on the same truth value as $A \wedge B$.

We say that $B \wedge A$ is logically equivalent to $A \wedge B$ and we can write this as follows $B \wedge A \equiv A \wedge B$

Definition: Two expression are logically equivalent if each one always has the same truth value as the other.

Also,

$$B \wedge A \equiv A \wedge B$$

$$B \vee A \equiv A \vee B$$

$$A \wedge (B \wedge C) \equiv (A \wedge B) \wedge C$$

$$A \vee (B \vee C) \equiv (A \vee B) \vee C$$

These equivalence reveal \wedge and \vee to be commutative and associative operations. But these are not the only important equivalences that hold between logical forms.

A	B	$A \rightarrow B$	A	B	$\neg A$	$\neg A \vee B$
F	F	(T)	F	F	T	(T)
F	T	(T)	F	T	T	(T)
T	F	(F)	T	F	F	(F)
T	T	(T)	T	T	F	(T)

In the last columns in tables (Shown Bracketed) we have exactly same sequences of truth values. So, $A \rightarrow B \equiv \neg A \vee B$. Thus, we could do without the operation \rightarrow .

Now, consider the following two truth tables.

A	B	$A \wedge B$	A	B	$\neg A$	$\neg B$	$\neg A \vee \neg B$	$\neg(\neg A \vee \neg B)$
F	F	(F)	F	F	T	T	T	(F)
F	T	(F)	F	T	T	F	T	(F)
T	F	(F)	T	F	F	T	T	(F)
T	T	(T)	T	T	F	F	F	(T)

We see from the bracketed truth values that $A \wedge B$ is logically equivalent to $\neg(\neg A \vee \neg B)$. Thus \wedge could be replaced by a combination of \neg and \vee .

Similarly we could show that \leftrightarrow can be replaced by a combination of \neg and \vee .

We say therefore that (\neg, \vee) forms a functionally complete set of connectives.

We can also show that (\neg, \wedge) also form a functionally complete set of connectives.

The NAND operator (\uparrow) by itself is also a functionally complete set. So is the Nor operator (\downarrow). These both are minimal functionally complete set.

Notice that (\vee, \wedge) is not a functionally complete set. Neither is (\neg) , (\vee) or (\wedge) by themselves functionally complete.

Example - 1.1

Obtain the truth table for $\alpha = (P \vee Q) \wedge (P \rightarrow Q) \wedge (Q \rightarrow P)$

Solution:

P	Q	$P \vee Q$	$P \rightarrow Q$	$(P \vee Q) \wedge (P \rightarrow Q)$	$Q \rightarrow P$	α
T	T	T	T	T	T	T
T	F	T	F	F	T	F
F	T	T	T	T	F	F
F	F	F	T	F	T	F

1.2.1 List of Important Equivalences

$A \wedge 0 \equiv 0$	Domination law	$A \cdot 0 \equiv 0$
$A \vee 1 \equiv 1$	Domination law	$A + 1 \equiv 1$
$A \wedge 1 \equiv A$	Identity of \vee	$A \cdot 1 \equiv A$
$A \vee 0 \equiv A$	Identity of \wedge	$A + 0 \equiv A$
$A \wedge A \equiv A$	Idempotence	$A \cdot A \equiv A$
$A \vee A \equiv A$	Idempotence	$A + A \equiv A$
$A \wedge \neg A \equiv 0$	Complement law	$A \cdot A' \equiv 0$
$A \wedge \neg A \equiv 1$	Complement law	$A + A' \equiv 1$
$\neg \neg A \equiv A$	Law of double negation	$(A')' \equiv A$
$A \wedge B \equiv B \wedge A$	Commutativity	$A \cdot B \equiv B \cdot A$
$A \vee B \equiv B \vee A$	Commutativity	$A + B \equiv B + A$
$A \vee (B \vee C) \equiv (A \vee B) \vee C$	Associativity	$A + (B + C) \equiv (A + B) + C$
$A \wedge (B \wedge C) \equiv (A \wedge B) \wedge C$	Associativity	$A \cdot (B \cdot C) \equiv (A \cdot B) \cdot C$
$A \wedge (B \vee C) \equiv (A \wedge B) \vee (A \wedge C)$	Distributivity	$A \cdot (B + C) \equiv A \cdot B + A \cdot C$
$A \vee (B \wedge C) \equiv (A \vee B) \wedge (A \vee C)$	Distributivity	$A + (B \cdot C) \equiv (A + B) \cdot (A + C)$
$A \wedge (A \vee B) \equiv A$	Absorption law	$A \cdot (A + B) \equiv A$
$A \vee (A \wedge B) \equiv A$	Absorption law	$A + (A \cdot B) \equiv A$
$\neg (A \wedge B) \equiv \neg A \vee \neg B$	De Morgan's law	$(A \cdot B)' \equiv A' + B'$
$\neg (A \vee B) \equiv \neg A \wedge \neg B$	De Morgan's law	$(A + B)' \equiv A' \cdot B'$
$A \rightarrow B \equiv \neg A \vee B$		$A \rightarrow B \equiv A' + B$
$A \leftrightarrow B \equiv (A \rightarrow B) \wedge (B \rightarrow A)$		$A \leftrightarrow B \equiv (A' \rightarrow B) \cdot (B' \rightarrow A)$

NOTE: \oplus (EX – OR) is commutative and associative, (NAND) and (NOR) are both commutative but not associative. $P \wedge (Q \oplus R) \equiv (P \wedge Q) \oplus (P \wedge R)$

Simplification

The various equivalence between logical forms provide us with a means of simplifying logical expressions. For example, we can simplify the logical forms.

$(A \vee 0) \wedge (A \vee \neg A)$ as follows:

$$\begin{aligned} (A \vee 0) \wedge (A \vee \neg A) &= A \wedge (A \vee \neg A) \\ &= A \wedge 1 \text{ (since } A \vee \neg A \equiv 1) = A \end{aligned}$$

$$\begin{aligned} \text{Similarly, } (A \wedge \neg B) \wedge (A \wedge B \wedge C) &\equiv A \wedge (\neg B \vee (B \wedge C)) \\ &\equiv A \wedge ((\neg B \vee B) \wedge (\neg B \vee C)) \\ &\equiv A \wedge (1 \wedge (\neg B \vee C)) \\ &\equiv A \wedge (\neg B \vee C) \end{aligned}$$

Since logic is a boolean algebra, it is always much easier to do simplification of logical expressions by converting them first into its boolean algebra equivalents.

Example: $(A \vee 0) \wedge (A \vee \neg A) \equiv (A + 0) \cdot (A + A') = (A) \cdot (1) = A$

Application to Circuit Design

One of most important application of Boolean algebra is to the design of electronic circuits and especially to the design of computer logic. The basic logic functions 'and', 'or' and 'not' can be realised by electronic devices called gates and these can be combined together to form complicated circuits. The 'and' connective is realised by an 'and-gate' which is symbolised as follows:




The idea is that if the AND-gate receives input signals on both the A and B input lines, there will be an output signal on the line marked $A \cdot B$. If there is no input on either A or B or both there will be no output signal. Similarly, an 'OR-gate' is symbolised as follows:




If there is an input signal on either A or B or both, there will be an output signal on $A + B$.

Finally a NOT gate looks alike



In this case, if there is an input A, there will be no output and If there is no input A, there will be an output. The input is said to be inverted or negated.

Similarly we have the NAND gate and NOR gate represented y represented by.



1.3 Well-Formed Formulas (WFFs)

Consider $P \wedge Q$ and $Q \wedge P$, where P and Q are any two propositions (logical statements). The truth table of these two propositions are identical. This happens when we have any proposition in place of P and any propositions in place of Q.

So we can develop the concept of propositional variable (corresponding to propositions) and well formed formulas (corresponding to propositions involving connectives).

Definition: A propositional variable is a symbol representing any proposition. We note that in algebra, a real variable is represented by the symbol x . This means that x is not a real number but can take a real value.

Similarly, a propositional variable is not a proposition but can be replaced by a proposition.

Definition: A well formed formula is defined as follows:

- (i) If P is a propositional variable then it is wff.
- (ii) If a is a wff, then $\neg a$ is a wff.
- (iii) If α and β are well formed formula, then $(\alpha \vee \beta)$, $(\alpha \wedge \beta)$, $(\alpha \rightarrow \beta)$, $(\alpha \leftrightarrow \beta)$ are well formed formula.

NOTE: A wff is not a proposition, but if we substitute the proposition in place of propositional variable, we get a proposition e.g., $(\neg P \wedge Q) \leftrightarrow Q$ is a wff.

Also note that " $P \neg \wedge Q \leftrightarrow Q$ " is not a wff. Similarly " $P \wedge Q \vee$ " is not a wff. This is because the above two cannot be derived using rules *i*, *ii* and *iii* given above for wffs.

Duality Law

Two formulas A and A' are said to be duals of each other, if either can be obtained from the other by replacing \wedge by \vee , \vee by \wedge , 0 by 1 (F by T) and 1 by 0 (T by F). e.g., Dual of $(P \wedge Q) \vee T$ is $(P \vee Q) \wedge F$, Dual of $A + 1 = 1$ is $A \cdot 0 = 0$

Let A and A' be duals consisting of P_1, P_2, \dots, P_n Propositional variables. By repeated application of De Morgan's Law, it can be shown that $\neg A (P_1, P_2, \dots, P_n) = A' (\neg P_1, \neg P_2, \dots, \neg P_n)$.

1.3.1 Truth Table for a Well-Formed Formula

If we replace the propositional variables in a formula α by propositions, we get a proposition involving connectives. The table giving the truth value of such proposition obtained by replacing the propositional variables by arbitrary proposition is called the truth table of α .

If α involves n propositional variables, we have 2^n possible combinations of truth values of propositions replacing the variables.

Tautology, Contradiction and Contingency

Definition: A **tautology** is a well formed formula whose truth value is T for all possible assignments of truth values to the propositional variables. Such a wff is also called valid (always true).

NOTE: When it is not clear whether a given formula is tautology, we can construct a truth table and verify that the truth value is T for all possible combinations of truth value of the propositional variables appearing in given formula.

Example - 1.2

Show that $\alpha = (P \rightarrow (Q \rightarrow R)) \rightarrow ((P \rightarrow Q) \rightarrow (P \rightarrow R))$ is a tautology.

Solution:

Truth table for α :

P	Q	R	$Q \rightarrow R$	$P \rightarrow (Q \rightarrow R)$	$P \rightarrow Q$	$P \rightarrow R$	$(P \rightarrow Q) \rightarrow (P \rightarrow R)$	α
T	T	T	T	T	T	T	T	T
T	T	F	F	F	T	F	F	T
T	F	T	T	T	F	T	T	T
T	F	F	T	T	F	F	T	T
F	T	T	T	T	T	T	T	T
F	T	F	F	T	T	T	T	T
F	F	T	T	T	T	T	T	T
F	F	F	T	T	T	T	T	T

Since the truth value of α is T for every possible combination of truth values of P, Q and R, we can say that α is a tautology.

Definition: A **contradiction** (or absurdity) is a wff whose truth value is F for all possible assignments of truth values to the propositional variables.

e.g., $P \wedge \neg P$ and $(P \wedge Q) \wedge \neg Q$ are examples of contradictions

Truth table for $P \wedge \neg P$

P	$\neg P$	$P \wedge \neg P$
T	F	(F)
F	T	(F)

Truth table for $(P \wedge Q) \wedge \neg Q$

P	Q	$P \wedge Q$	$\neg Q$	$(P \wedge Q) \wedge \neg Q$
T	T	T	F	(F)
T	F	F	T	(F)
F	T	F	F	(F)
F	F	F	T	(F)

Summary



- Two expressions are logically equivalent if each one always has the same truth value as the other.
- \oplus (EX – OR) is commutative and associative, (NAND) and (NOR) are both commutative but not associative. $P \wedge (Q \oplus R) \equiv (P \wedge Q) \oplus (P \wedge R)$
- A wff is not a proposition, but if we substitute the proposition in place of propositional variable, we get a proposition e.g., $(\neg P \wedge Q) \leftrightarrow Q$ is a wff.
- When it is not clear whether a given formula is tautology, we can construct a truth table and verify that the truth value is T for all possible combinations of truth value of the propositional variables appearing in given formula.
- A **contradiction** (or absurdity) is a wff whose truth value is F for all possible assignments of truth values to the propositional variables.
- A **contingency** is a wff which is neither a tautology nor a contradiction. In other words, a contingency is a wff which is sometimes true of sometimes false.
- Two wff a and b in propositional variables P_1, P_2, \dots, P_n are **equivalent** if the formula $a \leftrightarrow b$ is a tautology.
- For a given wff the PDNF form is unique the PCNF form is unique, if PDNF form or PCNF of 2 wffs are same, they are equivalent.
- Quantified parts of predicate formula such as $\forall x P(x)$ or $\exists x P(x)$ are propositions. We can assign values from the universe of discourse only to free variables in a predicate formula α .



Student's Assignments

- Q.1** The logical expression $((P \wedge Q) \Rightarrow (R' \wedge P)) \Rightarrow P$
- a tautology
 - a contradiction
 - a contingency
 - All the above

- Q.2** The principal conjunctive normal form is
- sum of products
 - product of sums
 - sum of max-terms
 - product of max-terms

- Q.3** Match **List-I** with **List-II** and select the correct answer using the codes given below the lists:

List-I

- Associative law
- Absorption law
- Demorgans law
- Commutative

List-II

- $P \vee (Q \vee R) \equiv (P \vee Q) \vee R$
- $P \vee Q \equiv Q \vee P$
- $\neg(P \vee Q) \equiv \neg P \wedge \neg Q$
- $P \vee (P \wedge Q) \equiv P$

Codes:

	A	B	C	D
(a)	1	2	3	4
(b)	4	3	1	2
(c)	1	4	3	2
(d)	2	1	4	2

- Q.4** Consider the following statements:

$$S_1: R \vee (P \vee Q)$$

is a valid conclusion from the premises

$$P \vee Q, R \rightarrow Q, M \rightarrow P \text{ and } \neg M$$

$$S_2: a \rightarrow b, \neg(f \vee c) \Rightarrow \neg b$$

then

- S_1 is true and S_2 is invalid
- S_1 is false and S_2 is invalid
- Both are true
- Both are false

Q.5 The following propositional statement is
 $[(p \rightarrow r) \wedge (q \rightarrow r)] \rightarrow [(p \vee q) \rightarrow r]$

- (a) tautology
- (b) contradiction
- (c) neither tautology nor contradiction
- (d) not decidable

Q.6 Identify the correct translation into logical notation of the following assertion

"All connected bipartite graphs are nonplanar"

- (a) $\forall x \left[\begin{array}{l} \sim \text{connected}(x) \vee \sim \text{bipartite} \\ (x) \wedge \sim \text{planar}(x) \end{array} \right]$
- (b) $\forall x \left[\begin{array}{l} \sim \text{connected}(x) \vee \sim \text{bipartite} \\ (x) \vee \sim \text{planar}(x) \end{array} \right]$
- (c) $\forall x \left[\begin{array}{l} \sim \text{connected}(x) \wedge \sim \text{bipartite} \\ (x) \wedge \sim \text{planar}(x) \end{array} \right]$
- (d) $\forall x \left[\begin{array}{l} \sim \text{connected}(x) \wedge \sim \text{bipartite} \\ (x) \vee \sim \text{planar}(x) \end{array} \right]$

Q.7 Which of the following statements are true?

- (i) It is not possible for the propositions $P \vee Q$ and $\neg P \vee \neg Q$ to be both false. To be both false.
- (ii) It is possible for the proposition $P \rightarrow (\neg P \rightarrow Q)$ to be false.
- (a) Only (i) is true
- (b) Only (ii) is true
- (c) Both (i) and (ii) are true
- (d) Both (i) and (ii) are false

Q.8 Which of the following statements are true?

- (i) $((P \rightarrow Q) \rightarrow R) \rightarrow ((R \rightarrow Q) \rightarrow P)$ is a tautology
- (ii) Let A, B be finite sets, with $|A| = m$ and $|B| = n$. The number of distinct functions $f : A \rightarrow B$ is there from A to B is m^n .
- (a) Only (i) is true
- (b) Only (ii) is true
- (c) Both (i) and (ii) are true
- (d) Both (i) and (ii) are false

Q.9 State whether the following statements are true or false?

- (i) $(P \Rightarrow Q) \Rightarrow (Q \Rightarrow P)$ always holds, for all proposition P, Q.
- (ii) $((P \vee Q) \Rightarrow Q) \Rightarrow (Q \Rightarrow (P \vee Q))$ always holds, for all propositions P.
- (a) (i) is true, (ii) is false
- (b) Both (i) and (ii) are true
- (c) (i) is false, (ii) is true
- (d) Both (i) and (ii) are false

Q.10 Which of the following is tautology?

- (a) $x \vee y \rightarrow y \wedge z$
- (b) $x \wedge y \rightarrow y \vee z$
- (c) $x \vee y \rightarrow y \rightarrow z$
- (d) $x \rightarrow y \rightarrow (y \rightarrow z)$

Q.11 Suppose

$P(x)$: x is a person.

$F(x, y)$: x is the father of y.

$M(x, y)$: x is mother of y.

What does the following indicates

$$(\exists z) (P(z) \wedge F(x, z) \wedge M(z, y))$$

- (a) x is father of mother of y
- (b) y is father of mother of x
- (c) x is father of y
- (d) None of the above

Q.12 Give the converse of "If it is raining then I get wet".

- (a) If it is not raining then I get wet
- (b) If it is not raining then I do not get wet
- (c) If it get wet then it is raining
- (d) If I do not get wet then it is not raining

Q.13 Which of the following is true?

- (a) $\neg(p \Rightarrow q) \equiv p \wedge \neg q$
- (b) $\neg(p \leftrightarrow q) \equiv ((p \vee \neg q) \vee (q \wedge \neg p))$
- (c) $\neg(\exists x (p(x) \Rightarrow q(x))) \equiv \forall x (p(x) \Rightarrow q(x))$
- (d) $\exists x p(x) \equiv \forall x p(x)$

Answer Key:

- 1. (c) 2. (d) 3. (c) 4. (a) 5. (a)
- 6. (b) 7. (a) 8. (d) 9. (c) 10. (b)
- 11. (a) 12. (c) 13. (a)



**Student's
Assignments**

Explanations

1. (c)

The logical expression
 $((P \wedge Q) \Rightarrow (R' \wedge P)) \Rightarrow P$
 can be converted in Boolean Algebra notation
 as,
 $(pq \Rightarrow r' p) \Rightarrow p$
 $\equiv ((pq)' + r' p) \Rightarrow p$
 $\equiv (p' + q' + r' p) \Rightarrow p$
 $\equiv ((p' + r' p) + q') \Rightarrow p$
 $\equiv ((p' + p) \cdot (p' + r') + q') \Rightarrow p$
 $\equiv (p' + r' + q') \Rightarrow p$
 $\equiv (p' + r' + q')' + p \equiv prq + p$
 $\equiv p$
 \therefore The given expression is a contingency.

4. (a)

$S_1 : P \vee Q, R \rightarrow Q, M \rightarrow P, \sim M \Rightarrow R \vee (P \vee Q)$
 In boolean algebra notation the above expression
 is written as
 $(p + q) \cdot (q + r') \cdot (p + m') \cdot m' \Rightarrow r + p + q$
 $\equiv (q + pr') (m') \Rightarrow r + p + q$
 $\equiv qm' + pr'm' \Rightarrow r + p + q$
 $\equiv (qm' + pr'm') + r + p + q$
 $\equiv (q' + m) (p' + r + m) r + p + q$
 $\equiv q'p' + q'r + q'm + mp' + mr + m + r + p + q$
 (by absorption law) $\equiv q'p' + r + m + p + q$
 $\equiv (p + p') \cdot (p + q') + r + m + q$
 $\equiv p + q' + r + m + q$
 $\equiv p + r + m + 1 \equiv 1$
 $\therefore S_1$ is true
 $S_2 : a \rightarrow b, \neg (f \vee c) \Rightarrow \neg b$
 In boolean Algebra notation
 $S_2 \equiv (a \rightarrow b) \cdot (f \vee c)' \Rightarrow b'$
 $\equiv (a' + b) \cdot (f'c') \Rightarrow b'$
 $\equiv [(a' + b) \cdot (f'c')] + b'$
 $\equiv (a' + b)' + (f'c')^1 + b'$
 $\equiv ab' + f + c + b'$
 $\equiv f + c + b'$
 which is a contingency
 $\therefore S_2$ is invalid.

5. (a)

$$\begin{aligned} & [(p \rightarrow r) \wedge (q \rightarrow r)] \rightarrow [(p \vee q) \rightarrow r] \\ & \equiv (p' + r) (q' + r) \rightarrow (p + q)' + r \\ & \equiv (r + p'q')' \rightarrow (p + q)' + r \\ & \equiv (r + p'q')' + (p + q)' + r \\ & \equiv r'(p'q')' + p'q' + r \\ & \equiv r'(p + q)' + p'q' + r \\ & \equiv r'p + r'q + p'q' + r \\ & \equiv (r + r') \cdot (r + p) + r'q + p'q' \\ & \equiv r + p + r'q + p'q' \\ & \equiv (r + r') (r + q) + (p + p') (p + q') \\ & \equiv r + q + p + q' \\ & \equiv r + p + 1 \equiv 1 \\ & \therefore \text{tautology} \end{aligned}$$

6. (b)

The correct translation is
 $\forall x[(\text{connected}(x) \wedge \text{bipartite}(x)) \rightarrow \sim \text{planar}(x)]$
 however, since $p \rightarrow q \equiv \sim p \vee q$, we can write
 the above expression also as,
 $\forall x[\sim \text{connected}(x) \vee \sim \text{bipartite}(x) \vee \sim \text{planar}(x)]$

7. (a)

If $P \vee Q$ is false, then both P and Q are false.
 So, $\neg P \vee \neg Q \equiv \neg F \vee \neg F \equiv T \vee T \equiv T$
 $\therefore (i)$ is true
 Consider (ii)
 $P \rightarrow (\neg P \rightarrow Q) \equiv P \rightarrow (P^1 \rightarrow Q)$
 $\equiv P \rightarrow P + Q$
 $\equiv P^1 + P + Q \equiv 1 + Q \equiv 1$
 It is a tautology, So (ii) is false.

8. (d)

(i) Using boolean algebra, we can shown that
 the given expression reduces to $P + R' + Q'$
 which is not a tautology.
 (ii) For each element $a \in A$, we have n possible
 choices for value of $f(a)$. Thus there are n^m
 possible functions.

9. (c)

$$\begin{aligned} (i) & (P \Rightarrow Q) \Rightarrow (Q \Rightarrow P) \\ & \equiv (P' + Q) \rightarrow (Q' + P) \\ & \equiv (P' + Q)' + Q' + P \\ & \equiv PQ' + Q' + P \equiv P + Q' \end{aligned}$$

Since $P + Q'$ is a contingency and not a tautology (i) is false

$$\begin{aligned}
 (ii) \quad & ((PVQ) \Rightarrow Q) \Rightarrow (Q \Rightarrow (PVQ)) \\
 & \equiv ((P + Q) \Rightarrow Q) \Rightarrow (Q \Rightarrow P + Q) \\
 & \equiv (P + Q)' + \Rightarrow Q \Rightarrow Q' + P + Q \\
 & \equiv P'Q' + Q \Rightarrow 1 + P \\
 & \equiv (Q + P') \cdot (Q + P') \Rightarrow 1 \\
 & \equiv (Q + P') \Rightarrow 1 \\
 & \equiv (Q + P')' + 1 \equiv 1 \\
 & \therefore (ii) \text{ always holds.}
 \end{aligned}$$

10. (b)

$$\begin{aligned}
 (i) \quad & x \vee y \rightarrow y \wedge z \equiv x + y \rightarrow yz \\
 & \equiv (x + y)' + yz \\
 & \equiv x'y' + yz \\
 & \not\equiv 1
 \end{aligned}$$

\therefore not a tautology

$$\begin{aligned}
 (ii) \quad & x \wedge y \rightarrow y \vee z \equiv xy \rightarrow y + z \\
 & \equiv (xy)' + y + z \\
 & \equiv x' + y' + y + z \\
 & \equiv 1 + x' + z \\
 & \equiv 1
 \end{aligned}$$

\therefore It is a tautology

$$\begin{aligned}
 (iii) \quad & x \vee y \rightarrow (y \rightarrow z) \equiv x + y \rightarrow (y \rightarrow z) \\
 & \equiv (x + y)' + (y \rightarrow z) \\
 & \equiv x'y' + y' + z \\
 & \equiv y' + z \\
 & \not\equiv 1
 \end{aligned}$$

\therefore not a tautology

$$\begin{aligned}
 (iv) \quad & x \rightarrow y \rightarrow (y \rightarrow z) \equiv x' + y \rightarrow (y' + z) \\
 & \equiv (x' + y)' + y' + z \\
 & \equiv xy' + y' + z \\
 & \equiv y' + z \\
 & \not\equiv 1
 \end{aligned}$$

\therefore not a tautology

13. (a)

Option (a) $\neg(p \Rightarrow q) \equiv p \wedge \neg q$ is true, since

$$\neg(p \Rightarrow q) \equiv \neg(p' + q) \equiv pq' \equiv p \wedge \neg q$$

◆◆◆◆◆